



Switch Commerce™

Std 3 TCP/IP DPL Wireless for Hyosung

Enter, Clear, Cancel, 1, 2, 3

1. Customer Setup

- Communication
 - TCP/IP
- Message Format
 - Standard 3 (Required)
- TCP/IP Type
 - SSL Option - Disabled
 - Standard TCP/IP
 - Status Monitoring - Enabled
 - Communication Header - Enabled
 - Communication ID - 123SC101
 - CRC - Disabled
- Select Processor or Select Host
- Standard 3 Option

2. Host Setup

- Use URL - Disabled
 - Host URL #1 - 192.168.0.52
 - Port #1 - 8000
 - Host URL #2 - 192.168.0.52
 - Port #2 - 8000
 - Host Address
- Disabled
- Secure Mode Password
 - Serial Number - 000000000000 or Terminal Serial # (if empty)
 - Key Mode - TDES
 - Edit Key
 - Key Index - 01
 - Key Entry - A/B
 - Key Index - 01
 - Key Entry - A/B
 - Key Part A
 - Key Part B
 - Password #1 - Default 11111111
 - Password #2 - Default 22222222
- Host Address

- Terminal ID - NH _____
 - Health Check Message – Enable for 2 Hours
 - Key Management
3. System Setup
- DHCP - Disabled (for Static IP)
 - IP Address - 192.168.0.55
 - Subnet Mask - 255.255.255.0
 - Default Gateway - 192.168.0.52
 - DNS - (Leave as is)
 - Terminal IP or ATM IP Setup

Exit out of Operator Functions, powerfail the ATM, look for the welcome screen try a test transaction.