



Std 3 TCP/IP Inhand for Hyosung

Enter, Clear, Cancel, 1, 2, 3

1. Customer Setup

- Select Processor or Select Host
 - Communication
 - TCP/IP
 - Message Format
 - Standard 3 (Required)
 - TCP/IP Type
 - SSL Option - Disabled
 - Visa Framed TCP/IP
- Standard 3 Option
 - Status Monitoring - Enabled
 - Communication Header - Enabled
 - Communication ID - 123SC101
 - CRC - Disabled

2. Host Setup

- Host Address
 - Use URL - Disabled
 - Host Address
 - Host URL #1 - 192.168.1.90
 - Port #1 - 7003
 - Host URL #2 - 192.168.1.90
 - Port #2 - 7003
- Terminal ID - NH _____
- Health Check Message
 - Disabled
- Key Management
 - Secure Mode Password
 - Password #1 - Default 11111111
 - Password #2 - Default 22222222
 - Serial Number - 0000000000000 or Terminal Serial # (if empty)
 - Key Mode - TDES
 - Edit Key

- Key Part A
 - Key Index - 01
 - Key Entry - A/B
- Key Part B
 - Key Index - 01
 - Key Entry - A/B

3. System Setup

- Terminal IP or ATM IP Setup
 - DHCP - Disabled (for Static IP)
 - IP Address - 192.168.1.91
 - Subnet Mask -255.255.255.0
 - Default Gateway - 192.168.1.90
 - DNS - (Leave as is)

Exit out of Operator Functions, powerfail the ATM, look for the welcome screen try a test transaction.