



Switch Commerce™

Std 3 TCP/IP Inhand for Genmega

Enter, Clear, Cancel, 1, 2, 3

1. System Setup
 - Serial Number
 - Change Serial Number
2. Customer Setup
 - Change Processor
 - SSL Activation - (Not necessary if SSL is activated)
 - Enter SSL Activation Code
 - Communication – Visa Framed
 - Message Format - Standard 3
 - Standard 3 Option
 - Comm Header - Enabled
 - Status Monitoring - Enabled
 - 12 Seq Number - Disabled
 - Use TCP/IP CRC - Disabled
3. Host Setup
 - Host IP Address
 - Host IP Address - 192.168.1.90
 - Host Port - 7003
 - Configuration - Scheduled
 - Routing ID
 - Change Routing ID - 123SC101
 - Terminal Number
 - Change Terminal # - TX_ _ _ _ _
 - Key Management
 - Enter Secure Passwords #1 & #2
 - Key Mode
 - TDES
 - Edit Master Key
 - Key Part A
 - Key Index - 01
 - Key Entry - A/B
 - Key Part B
 - Key Index - 01

- Key Entry - A/B

4. System Setup

- Device Setup
 - ATM TCP/IP Setup
 - TCP/IP Mode - Static IP
 - IP Address - 192.168.1.91
 - Subnet Mask - 255.255.255.0
 - Default Gateway - 192.168.1.90
 - Push APPLY to save changes

Exit out of Operator Functions, look for the welcome screen and try a test transaction.